

Index	Änderung	Datum	Name
01.00	Erstellung dieser Kurzbeschreibung	13.12.2012	Skrebba

## Aufgabe

Es soll ein virtueller COM-Port für das LAN-Modem installiert und eingerichtet werden. Benötigt wird dafür der "COM-Port Redirector" von Lantronix.

Nach der Installation und Konfiguration ist es möglich, mit dem über LAN angeschlossene Modem, über die ausgewählte Com-Schnittstelle zu kommunizieren, so, als wäre es ein serielles Modem.

## Installation des "COM-Port Redirector"

Laden Sie sich bitte von der <u>Lantronix-Homepage</u>, den für Ihr Betriebssystem neuesten "Redirector" und installieren Sie diesen bitte, unter Beachtung der dabei angezeigten Hinweise.

## Einrichtung und Konfiguration

Stellen Sie sicher, dass die eingestellte IP-Adresse des LAN-Modem, zu Ihrem Netzwerk "passt" und schliessen Sie es an Ihrem Netzwerk an.

Überprüfen Sie bitte, ob im Lan-Modem unter "Connection / Common Options", der "Telnet Com Port Cntrl", auf "Disable" gesetzt ist.

Starten Sie den "COM-Port Redirector" (CPR Manager). Betätigen Sie dann den Button "Search for Devices".

S CPR Manager 4.3.0.1														
File Com Port Device	Tools	Help												
🛛 Add/Remove 🛛 🛃 Save	Refresh	🔎 Search For Devices 🧯	Exclude											
Com Ports	Hide 🤤	Com Port List												
E- All Com Ports (2)		Com Port	IP Address	TCP Port	Com Status	Network Status		2217	BirWr	SvrRec	NoCla	CntTO	TORec	KpAlv
Com 3 - 4 Com 3 (Inaccessible)		Com 3 (Inaccessible) Com 4 (Marked for D	. 192 168 0 19	10001	Ocsed	Disconnected			Yes			7	Yes	
• / m	,	×												
evice List														Collapse
IP Address #	Ports TCP	Port Product	ID	HW Address	N	twork interface	Device Name		P	ort Name				
192.168.0.19 1	1000	1 XPort-03/04	75	00:20:4A:DF:E	EA:08 19	12.168.0.1	Test		1	0001				
Ready												Hodif	ied	

Das LAN-Modem sollte dann, mit seiner IP, im unteren Teil des Fensters aufgeführt sein.

Betätigen Sie dann bitte den Button "Add/Remove COM Ports" und wählen Sie einen COM-Port aus, der noch nicht von Ihnen belegt ist. Betätigen Sie dann den "OK" Button.



Max         North         Control         Cont	: KpAv
2217         BH%         Sufface         Nachs         Oct10         TORec           Cont41         Cont61         Cont101         Cont121         Yes         7         Yes           Cont42         Cont82         Cont102         Cont12         Yes         7         Yes           Cont41         Cont84         Cont102         Cont123         Yes         7         Yes           Cont44         Cont84         Cont104         Cont103         Cont123         Yes         7         Yes           Cont44         Cont84         Cont104         Cont105         Cont105<	: KpAv
Condit         Condit<	: KpAv
Com59 Com79 Com199 Com119 Com129 Com60 Com100 Com100 Com120 Com140	
Check (Range) 1	Collaps
B Uncheck (Range) 1 1 1 256 1	
10001	
	Uncheck (Range), 1 (b) 125 (c) Nume Por Name 10001

Anschliessend gehen Sie bitte mit der rechten Maustaste auf des LAN-Modem unter Device-List und wählen Sie "Add to settings".

All Com Ports	Save Refr H	ide 🥥	Search For Devices 😂 Exclu Settings Com 5 (New)	de					
Com 3 - 5 Com 3 Com 3 Com 4 Com 5	(Inaccessible) (Marked for D (New)	eletion	Window's Port Name: Window's Device Name: Window's Service Name:			Com Status: C Network Status: D	losed		
			Reset to Defaulta	Cancel	Edits				
			Euffer Writes (Keep of Server Reconnect No Net Close	ecked for b	etter write performance )	7 Co	nnection Timeout (in seco ect 0 🚱 Reconnect	nds) LLimit (0 = forever)	
			Listen Mode	Normal -	port closed after disconnec	t - TCP	Port	dd To Firewall	
			TCP KeepAlive	7200000	KeepAlive Time (ms	ec) 1000 🗄 KeepAlm	ve Interval (meec)		
			IEI BEC 2217 DTB (In)	Tie DTR	to DCD; DSR always activ	- 10			
			(TruPort)						
			Service   Nost   1 (101 Pont ) 1 192,168.0.19 10001  2			WARNING! If the Host firewall, then UDP ports added to the firewall's o opening this com port if	is on the other side of 30718, 43282 and 43 scclusion list. You may these UDP ports are n	a router or a 283 may need to be experience trouble tot excluded.	
			2						
			2 3 4 5 6 7			Also, some legacy devi you are unable to conn cause is the Firewall or the 'Add Rx Port' buttor button caption reads 'R been added and can be	ce servers respond on ect to a device server, this machine is blocki to add this part to the lemove Rx Port' then the removed by pressing	UDP port 43283. If one possible no this port. Press. E firewall. If the e port has already. this button.	
			2 3 4 5 6 7 8			Also, some legacy devi you are unable to commo cause is the Firewall or the 'Add Rx Port' button button caption reads 'Th been added and can be Remove Rx Po	ce servers respond on ect to a device server, this machine is block to add this port to the server. Rx Port then the removed by pressing of the Firewall is to	UDP port 43283. If one possible in this port. Press. Finewall. If the is port has already, this button, med OFF	
		-	2 3 4 5 6 7 8			Also, some legacy devi you are unable to com cause is the Firewall on the "Add Rr Port" button batton cacito mesda. "I been added and can be Remove Rx Po	ce servers respond on net to a device server, this machine is block to add this port to the server & Port then the removed by pressing to the Firewall is to	UDP port 43283. E one possible one possible needs and the port free set has already. the batton. med OEE	
noe List Ardreas	# Posts	TCP Port	2 3 4 5 6 7 8	10	Will Address	Also, some legacy devi you are unable to come the 'Add Re Port' batto bitter cattor mada. The been added and can be Remove Rx Port Natwork Interface	ce servers respond on ect to a device server; this machine is block to add this port to the move R P or then it removed by pressing The Firewall is to Device Name	UDP.port 43283_IF one bookble press. Finewall_IF. Finewall_IF. In the port han already. has botton.	Collaps
m te List iddess ₩ 152.168.0.19	# Pots	TCP Port 10001	2 3 4 5 6 7 8 Product XPor 63/04	10 X5	HW Address 00 20 4A DF EA 08	Also, some lesaery devir you are unable to come the "Add Be off botto botton cashion reads." Remove Rx Po Network Interface 192.168.0.1	Do servers respond on. text to a divise server, this machine is block to add this cort to the servers Rx Port then it removed by pressional rt The Firewall is to Device Name Test	UDP sort 42283 If one possible one possible foread II the on ord has already his lattice. Port Name 10001	College
m ve Lisst ddress 2152, 168, 0, 19	# Pots 1	TCP Port 10001	2 3 4 5 5 6 7 8 8 Product XPore(3):04	10 XS	HW Address 00 20 4A DF EA 08	Also, some lessers device rost att strabile to comme the "Add Be off-botto batton caetion made. R Remove Rx Po Network Interface 192.168.0.1	De servers respond on. end to a device server, this machine is block to add this perit to the server Rr. Port Then it removed by pressing. The Firewall is to Device Name Test	UDP sort 4283. If one possible one possible Freesal. If the need of the bas lattice. Need OFF Pot Name 10001	Collap
m te List tddreas 152:168.0.19	# Pots 1	TCP Port 10001	2 3 4 5 5 6 7 7 8 8 8	10 X5	HW Address 002044.0FEA.08	Also, some frozers device resu are unable to corre- cause is the Firewall or the "Add Revol" batten batten capition made. The Been added and can be Remove Rx Re Remove Rx Re Network Interface 192,168.0.1	ex. servers research on. et lo a device server; this mochains estrong; the add this port to the servers for Lord' then it to the add this port to the servers for greensing. The Firewall in to Device Name Test	UICP cost 42283. I rost pessible. To this cost. Threas out person the second second has battery. Part Name Port Name 10001	Collap
m ze List ddress 192, 168, 0, 19	# Pots 1	TCP Port 10001	2 3 4 5 6 7 8 7 8 7 8 7 8 7 8 7 8 7 8 7 8	10 X5	HW Adms 0020 4ADFEA08	Aleo, sene livear: drive ma are unable to corro cause is the Freevall or the "Add Re Port I batton batton causton results" men added and can be nabled and can be Remove Rv. Rv Network: htelace 192, 168,0.1	ex servers respect don est to a device server, this mechanism is blocks to add this point to the servers for fact there is no the fact the fact the point of the fact the fact the fact the fact the point of the fact the fact the fact the fact the point of the fact the fact the fact the fact the point of the fact the fact the fact the fact the fact the point of the fact the fact the fact the fact the fact the point of the fact the	URD peod 42833 I on peodde Peods Interest II the peod has been been defer Poot Name 10001	Collap
m te List dd≉ess ≝ 152.168.0.19	#Pots 1	TCP Port 10001	2 3 4 5 6 7 8 Product 30 4 5 5 6 5 7 8 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5	10 XS	HW Adms 00204ADFEA08	Aleo, some lonarat eller men ann sunder lon corre cause is the Terrention of the Terrention the Sold Tile Aroch Sautore been added and can be construction of the Sautore (Renove Ry Re Network Hotelsce 192168.01	ex servers respect don to a device server, this mechanism is blocks to add this point to the servers for fact there is no to add the servers are removed for servers are removed for servers and the Firewall in to Device Name Test	UDP peod 42623 I on peodde. To the and the set of the s	Cottap

Anschliessend betätigen Sie den "Save" Button und bestätigen mit "Yes".

Für das LAN-Modem in diesem Beispiel haben Sie nun den virtuellen COM-Port "Com5" festgelegt.



File ComPort I	levice To	ols Help								
Add/Remove	iave 🔄 Re	fresh P	Search For Devices	Exclude						
Com Ports		Hide 🥥	Settings Com 5 Tests							
ar com Potte (2) ar Com 3 - 5 -∞ Com 3 (naccessible) -∞ Com 5			Window's Port Name Window's Device Na Window's Service N	Lantronix me: ÜbeviceiC ime: CprDrvr	antronix CPR Port (COM5) DevicelCptDevice5 (prDvv Cancel Edits		Com Statua: Closed Network Statua: Disconnected			
			Server Reconner	t t	r beder write	e performance )	Timeout Reconnect	t 0 0 Reconnect	nds) : Limit (0 – forever)	
			E Listen Mode	Noma	l - port close	d after disconnect	+ TCP P	art Ad	id To Firewall	
			TCP KeepAlive	72000	00 👘 Kee	Alive Time (maed	:) 1000 👘 KeepAlive	Interval (meec)		
			CTruPort)	R (In) Tie D1	TR to DCD. I	DSR always active				
			Service Host 1 192.168.0.19 2			1 TOP Par S NA		on the other side of a 0718, 43282 and 43 Jusion list. You may see UDP ports are n	a router or a. 283 may need to be experience trouble ot excluded.	
			3 4 5 6				liso, some legacy device ou are unable to connec ause is the Firewall on th w 'Add Rx Port' button t utton caption reads 'Rer een added and can be r	servers respond on 1 to a device server, his machine is blockin add this port to the nove Rx Port' then the moved by pressing t	UDP port 43283. If one possible ng this port. Press. Firewall. If the e port has already his button.	
			8				Remove Rx Port	The Firewall is ha	mod QEE	
having list										Collance
P Address	# Ports	TCP Port	Product	10	HW A	idress	Network Interface	Device Name	Port Name	complete
See 192, 168, 0, 19	1	10001	XPort-03/04	)(5	5 00:20	4A:DFEA:08	192.168.0.1	Test	10001	

## Test

Wählen Sie dann, "Com X Tests" aus. X steht in diesem Beispiel für 5.

File Com Port											00
	Device Tor	ols Help									
Add/Remove	Save 💽 Re	fresh 🔎	Search For Dev	ces 🤤	Exclude						
Com Ports		Hide 🥥	Settings Com	Tests							
Al Com Ports Com 3 - S - Com 3 - S - Com 5 - Com 5	(2) (Inaccessible	•)	Open Obse Help RS232 High Low Rx Data Rx EOF 0		in 5 DSR	Com Netw	Status: Closed ork Status: Disconnected eOUT> RTS DTR O O O TTS M: OTR H: TTS Le: OTR Le:				
evice List											Collapse
ievice List IP Address	# Pots	TCP Post	Product			10	HW Address	Network Interface	Device Name	Port Name	Collapse
evice List P Address 192 168 0 19	# Pots 1	TCP Port 10001	Product XPort-03/04			1D X5	HW Admss 00:20:4A:DF:EA:08	Network Interface 192.168.0.1	Device Name Test	Pot Name 10001	Collegee
evice List P Address See 152 158 0.19	# Pots 1	TCP Pot 10001	Product XPot-03/04			10 X5	HW Address 00204ADFEA08	Network Interface 152-168.0.1	Device Name Test	Pot Name 10001	Cellapse
evice List P Address See 152 168 0 19	# Pots 1	TCP Pot 10001	Product XPort-03/04			1D X5	HW Address 00 20 AA DF EA 08	Network Interface 152, 168 0, 1	Device Name Test	Pot Name 10001	Collegee
Verkoe List IP Address See 152 158 0.19	# Pots 1	TCP Port 10001	Product XPort-03/04			10 X5	HW Address 00.20 4A.DF.EA.08	Network Weeface 192.168.0.1	Device Name Test	Pot Name 10001	Collegoe
verker List IP Address See 152 158.0 19	# Pots 1	TCP Port 10001	Product XPort-03/04			10 X5	HW Address 00204A.DF.EA.08	Network Interface 192, 1650, 1	Device Name Test	Pot Name 10001	College
Verke List IP Address 192 193 0 19	# Pots 1	TCP Pot 10001	Product XPort-03/04			10 X5	HW Address 0020AA.DF.EA.08	Network Interface 192, 1680, 1	Device Name Test	Pot Name 10001	Collegue
Hevice List IP Address Status 152, 168,0,19	# Pots 1	TCP Pot 10001	Product XPort-03/04			10	HW Address 00:20 4A DF EA 08	Network Interface 192 165 0 1	Device Name Test	Post Name 10001	Collapse
Verker List IP Address See 152 168.0.19	# Pots 1	TCP Pot 10001	Product XPost-03/04			0 10	HW Address 00.20 AA.DF.EA.08	Network Heeface 192, 168 0, 1	Device Name Test	Por Nerre 10001	Cutepse
entre Lat IP Address 152 158 0 19	# Pots 1	TCP Pot 10001	Product XPort-03/04			D X5	HW Address 0020 AA DF EA 08	Network Interface 192, 1680, 1	Device Name Text	Port Name 1001	Collapse

Um zu testen, ob die Einrichtung des virtuellen COM-Ports erfolgreich war, starten Sie nun ein beliebiges Terminalprogramm auf Ihrem PC und wählen dort, den zuvor festgelegten COM-Port, in diesem Beispiel Com5 aus.

Öffnen Sie dann bitte die Schnittestelle.



S CPR Manager 4.3.0.						ED 100 122	A.
File ComPort D	levice To	ools Hel	2				bCel , A
Add/Remove	ave 🖹 Ra	efresh 🔎	Search For Devices 😄 Exclude	e			rsch Formativorlagen Andern v
Con Ports	2) Inaccentral	Hide 🤤	Setting         Con 1 Test           Help         Open           HS22         Con 1 Test           SETE         Con 1 Test           HS23         Con 1 Test           SETE         Con 1 Test           High         Open           High         Con 2 Test           High         Con 2 Test           High         Con 2 Test           High Con 0         Con 2 Test           High Con 0         Con 2 Test           High Con 0         Con 2 Test	Com Neto	Salua: Open sk Statu: Connected 1 eOUT> RTS GTR O O O O O O O O O O O O O O O O O O TTS H, DTR H, ITS LD O TTR LD	NE MAD 19 10001	(a)
						B Tenind Dicercent He Cole Seed Refle Taffie Hen. Day	Reset Ore
evice List							
IP Address	# Ports 1	TCP Per 10001	Product XPart 03/04	1D X5	HW Address 00 20 4A: DF EA:08		
						COMB 900,010 No handsh. ASCI VTI20 Echo off Messager	4 🖬
Status of Com Port 5 is	Closed and	Disconnec	ted			Messages 🏴 Find in Files	
						Insert	

Sie sehen nun im CPR Manager, dass sich der Status geändert hat und das LAN-Modem virtuell mit dem ausgewählten COM-Port verbunden ist.

Sie können nun direkt über dem Terminalprogramm mit dem LAN-Modem mittels Modem spezifischer AT-Kommandos kommunizieren.

S CPR Manager 4.3.0	1					A.
File Com Port	Device To	ols Help				Ccl A
😺 Add/Remove 🔛	Save 🔄 Re	fresh 🔎	Search For Devices 😅 Exclude			rsch v Formatvorlagen
Com Ports		Hide 🥥	Settings Con 5 Tests			9
● 2 A Can Pers ● Can 3 - 2 ● Can 5	(2) Draccessibil		Mark         Court         Cu           Mark         Court         Cu           REAL         Reaction         Reaction           Mark         Court         Cu           Mark         Court         Cu	m Simur Open tenet Status Connected FIG OTF CON CON CON CON MTSLA OTFLA	10 10 10 1001      Contribution     Contribution	(C Testoo
Province 1 and					0	
Lievee Les	-	100.0-4	Part 10	1001 546444	4	
IP ADDRESS	# Ports	TLP Pot	Moduli II	J HW Address		
192 198 0.19	1	10001	AP66-03/04 3	S 00204ADEEA08		
						*
					COM5: 9600,8NI No handsh. ASCII VT100 Echo off	
					Merrages	平 🖾
					Eron 🛅 Warings	
					Messages #D Find in Files	