GSM Scout GPS





Simply supervising with your mobile, SMS event messaging as well as GPS positioning - immediately informed, immediately reaction!

Gesellschaft für Telekommunikation

Order no.: 700100210S

Applications

Supervising of:

- Sailing vessel, boats and yachts
- Camper and Caravans
- Homes

GPS positioning:

- Setting of berthing place by pressing a button
- Automatical messaging by SMS on leaving the berth place
- Request of the latest GPS position by SMS

Telemetry of electrical devices:

- Bilge pump
- Light
- Cooler



General informations

The scout GSM is an inexpensive and easy solution for the supervision of movable objects like boats, yachts, caravans or campers as well as the supervising of homes. Over connected sensors the device grasps, e.g., burglaries, upcoming fire, water or other serious events. These are immediately sent by SMS to any mobile phone and the user is able to initiate immediately countermeasures. The system is simply configurable about the phone number memory of the SIM-card and is ready for use immediately.

Further it is possible to activate the relais outputs by an SMS. So the user is able to switch different devices on board on or off. Bz GPS is it possible to localiye the position of the GSM Scout and the supervised object. The position will be sended as an SMS.

Technical specific features

- Comfortable connection about screw contacts
- No special software necessary
- The easy configuration about SIM-card
- Small construction style
- 2 relais contacts for switching devices
- Customizable event messages
- GPS positioning via SMS

Conditions

Fon: +49 (0)3303 - 409 639 Fax: +49 (0)3303 - 409 691

To use the scout GSM, you need:

Power supply, activated SIM-card (prepaid or fix contract), Sensors

Technical data

GSM networks 900 & 1800 Mhz or 850 & 1900 Mhz networks

Configuration Programming of the SIM-card over the mobile phone

Physical Dimensions / $100 \times 90 \times 25 \text{ mm}$ (L x H x W) / 140 g

weight

- 30 °C bis + 60 °C work temperatur Temperature range

Interfaces 1 registration circle for "burglary"

1 registration circle for "fire" 1 registration circle for "water"

1 registration circle for "arbitrary event"

2 relais contacts

11 - 35 V DC, 90 mA **Energy supply**

GSM Scout GPS Scope of supply

Manual

Miniatur screw driver

Optionale accessories

Mains Power Supply 12 V DC 305307214 300303304\$

Glass Attached Antenna (Indoor use),

1,5 m cable (SMA) 300303310S Round Antenna PUK (Outdoor use),

web: www.coniugo.com

e-mail: hit@coniugo.com

3 m cable (SMA) Various sensors on request

06/2014

Order-No.