# **GSM Scout Professional**





Monitoring, remote control and optional position tracking by SMS from your cell phone - direct informed, direct reaction

ConiuGo GmbH Gesellschaft für Telekommunikation

Order no.: 700100214S

## **Applications**

#### Monitoring of:

- Heatings, reefers and server rooms
- Buildings and objects
- Plants and machines
- Boats, yachts, campers and caravans
- Home

#### Remote switching of:

- Bilge pump
- Light
- Air conditioner



#### General information

The GSM Scout Professional is a professional solution for monitoring objects. The device detects e.g. Burglary, upcoming fire, entrance of water, or other fundamental indidents, with its connected sensors. Those are sended immediately by SMS to a chosable cell phone, which allowes direct reaction. The system is easy to customize with the dial number storage of the SIM card and instant ready to use. Furthermore it is possible to activate the relais output by SMS. That makes switching on or off possible, for a huge number of devices. An optional extension is the tracking by SMS. The GSM Scout Professional is able to detect ist position and sending an SMS, in the case of unauthorized movements.

#### Technichal features

- Easy installation with screws
- No special software required
- Easy setting bei SIM card
- Transmitting of credits for prepaid SIM card
- Transmitting of the signal quality
- Different alarm texts possible
- Programming by SMS
- Internal lithium polymer battery
- Position tracking by SMS, geofencing (optional)

### **Conditions**

Fon: +49 (0)3303 - 409 639 Fax: +49 (0)3303 - 409 691

For using the GSM Scout Professional is required: SIM card (prepaid or contract), sensors

#### Technical data

Mobile network Usable with all european mobile providers, others

on request

**Customization** SIM card programming by cell phone

Dimensions / weight  $110 \times 100 \times 75 \text{ mm}$  (W x L x H) / 219 g

**Temperature range**  $-30 \,^{\circ}\text{C}$  up to  $+60 \,^{\circ}\text{C}$  working temperature

**Interfaces** 1 circuit for "burglary"

1 circuit for "fire"
1 circuit for "water"

1 circuit for "configurable incident" 2 x relais switching contacts NO

**Power supply** 11 - 35 V DC , 90 mA - 130 mA,

internnal lithium polymer battery

**Scope of delivery** GSM Scout Professional

Manual

Miniature screw driver Screws for housing mounting

 Optional accessoires
 Order no.

 Power supply 230 V AC / 12 V
 305307214

Power supply 230 V AC / 12 V 305307214 DCGlass attached antenna (indoor), 300303304S

1.5 m calel (SMA)

Round antenna PUK (outdoor), 300303310S

3 m calel (SMA)

GPS receiver (fexternal applications)
R/C R/C protection combination 700100618

web: www.coniugo.com

e-mail: hit@coniugo.com

Diverse Ssensords on request

06/2014